

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
5 August 2004 (05.08.2004)

PCT

(10) International Publication Number
WO 2004/065977 A1

(51) International Patent Classification⁷: **G01R 33/565,**
33/561

(21) International Application Number:
PCT/IB2003/006306

(22) International Filing Date:
15 December 2003 (15.12.2003)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
03100115.9 21 January 2003 (21.01.2003) EP

(71) Applicant (for all designated States except US): KONIN-
KLIJKE PHILIPS ELECTRONICS N.V. [NL/NL];
Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).

(72) Inventor; and

(75) Inventor/Applicant (for US only): FUDERER, Miha
[BE/NL]; c/o Prof. Holstlaan 6, NL-5656 AA Eindhoven
(NL).

(74) Agent: COHEN, Julius, S.; Philips Intellectual Property
& Standards, Prof. Holstlaan 6, NL-5656 AA Eindhoven
(NL).

(81) Designated States (national): AE, AG, AL, AM, AT, AU,
AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR,

CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD,
GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR,
KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN,
MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU,
SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA,
UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.


(84) Designated States (regional): ARIPO patent (BW, GH,
GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW),
Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM),
European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE,
ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE,
SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA,
GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Declaration under Rule 4.17:

— as to applicant's entitlement to apply for and be granted
a patent (Rule 4.17(ii)) for the following designations AE,
AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ,
CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE,
EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN,
IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV,
MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM,
PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ,
TM, TN, TR, TT, TZ, UA, UG, UZ, VC, VN, YU, ZA, ZM,
ZW, ARIPO patent (BW, GH, GM, KE, LS, MW, MZ, SD,
SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY,
KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG,

[Continued on next page]

(54) Title: MAGNETIC RESONANCE METHOD WITH NON-LINEAR MAGNETIC FIELD GRADIENTS



(57) Abstract: A magnetic resonance imaging method is presented for forming an image of an object, wherein a stationary magnetic field and temporary magnetic fields having a position dependent field pattern are applied, magnetic resonance signals are acquired by at least one receiver antenna, spins are excited in a part of the object, MR signals are acquired during application of the position-dependent field patterns (G_1 , G_2, \dots) and a magnetic resonance image is derived from the sampled magnetic resonance signals. The field patterns are substantially non-linear, the number N of total field patterns is larger than 3, and at least $N-1$ field patterns are independently controllable in field strength. The magnetic resonance signals are acquired in a sub-sampling fashion.

BEST AVAILABLE COPY



CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT,
LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ,
CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD,
TG)

— before the expiration of the time limit for amending the
claims and to be republished in the event of receipt of
amendments

Published:

— with international search report

For two-letter codes and other abbreviations, refer to the "Guid-
ance Notes on Codes and Abbreviations" appearing at the begin-
ning of each regular issue of the PCT Gazette.

- applying of a stationary magnetic field and temporary magnetic position-dependent field patterns,
- excitation of spins in a part of the object,
- acquiring magnetic resonance signals by one or more receiver antennae,
- and MR signals are acquired during application of the position-dependent field patterns.

Current MR systems are usually very limited in size of the useable imaging region which is dependent on the homogeneity volume of the main stationary magnetic field. In this volume the main magnetic field has to obey stringent aims on constancy and the three temporary magnetic gradient fields have to obey stringent aims with respect to linearity. Increasing the volume of the main magnetic field, where the field is substantially constant and the normal gradients are substantially linear, makes the system extremely expensive.

This object of the invention are achieved by a method as defined in Claim 1.

20 The invention is further related to an apparatus as defined in Claim 6 and to a computer program product as defined in Claim 9.

25 These and other advantages of the invention are disclosed in the dependent claims and in the following description in which an exemplified embodiment of the invention is described with respect to the accompanying drawings. Therein shows:

Fig. 1 diagrammatically a magnetic resonance imaging system in which the present invention is used,

Fig. 2 a one-dimensional object acquired with two field-patterns,

Fig. 3 the x-component of the field caused by the two field patterns,

5 Fig. 4 the locus of the object-space in G-space,

Fig. 5 folding of the object-locus in G-space due to undersampling,

Fig. 6 the position dependent field patterns of four conductor systems,

Fig. 7 the locus of the object in G-space,

Fig. 8 the same locus as in Fig. 7 with a single measurement point, and

10 Fig. 9 the same locus as in Fig. 7 with several measurement points.

Fig. 1 shows diagrammatically a magnetic resonance imaging system in which the invention is used. The magnetic resonance imaging system includes a set of main coils 10 whereby the steady, uniform magnetic field B_0 is generated. The main coils are constructed, for example in such a manner that they enclose a tunnel-shaped examination space. The patient to be examined is slid into this tunnel-shaped examination space. The magnetic resonance imaging system also includes a number of field pattern coils 11, 12 whereby magnetic fields exhibiting spatial variations, notably in the form of temporary position-dependent field patterns in individual directions, are generated so as to be superimposed on the uniform magnetic field. The field pattern coils 11, 12 are connected to a controllable power supply 21. The field pattern coils 11, 12 are energized by application of an electric current by means of the power supply unit 21. The strength, direction and duration of the field patterns are controlled by control of the power supply unit. The magnetic resonance imaging system also includes transmission and receiving coils 13, 15 for generating the RF excitation pulses and for picking up the magnetic resonance signals, respectively. The transmission coil 13 is preferably constructed as a body coil whereby (a part of) the object to be examined can be enclosed. The body coil is usually arranged in the magnetic resonance imaging system in such a manner that the patient 30 to be examined, being arranged in the magnetic resonance imaging system, is enclosed by the body coil 13. The body coil 13 acts as a transmission aerial for the transmission of RF excitation pulses and RF refocusing pulses. Preferably, the body coil 13 involves a spatially uniform intensity distribution of the transmitted RF pulses. The receiving coils 15 are preferably surface coils 15 which are arranged on or near the body of the patient 30 to be examined. Such surface coils 15 have a

high sensitivity for the reception of magnetic resonance signals which is also spatially inhomogeneous. This means that individual surface coils 15 are mainly sensitive for magnetic resonance signals originating from separate directions, i.e. from separate parts in space of the body of the patient to be examined. The coil sensitivity profile represents the spatial sensitivity of the set of surface coils. The receiving coils, notably surface coils, are connected to a demodulator 24 and the received magnetic resonance signals (MS) are demodulated by means of the demodulator 24. The demodulated magnetic resonance signals (DMS) are applied to a reconstruction unit 25. The reconstruction unit reconstructs the magnetic resonance image from the demodulated magnetic resonance signals (DMS), on the basis of the coil sensitivity profile and the knowledge of the fields of the temporary field patterns of the set of surface coils. The coil sensitivity profile is stored, for example electronically, in a memory unit which is included in the reconstruction unit. The reconstruction unit derives one or more image signals from the demodulated magnetic resonance signals (DMS), which image signals represent one or more, possibly successive magnetic resonance images. The reconstruction unit 25 in practice is preferably constructed as a digital image processing unit 25 which is programmed so as to reconstruct the magnetic resonance image from the demodulated magnetic resonance signals and on the basis of the coil sensitivity profiles and the knowledge of the fields of the temporary field patterns. The image signal from the reconstruction unit is applied to a monitor 26 so that the monitor can display the image information of the magnetic resonance image (images). It is also possible to store the image signal in a buffer unit 27 while awaiting further processing, for example printing in the form of a hard copy.

In order to form a magnetic resonance image or a series of successive magnetic resonance images of the patient to be examined, the body of the patient is exposed to the magnetic field prevailing in the examination space. The steady, uniform magnetic field, i.e. the main field, orients a small excess number of the spins in the body of the patient to be examined in the direction of the main field. This generates a (small) net macroscopic magnetization in the body. These spins are, for example nuclear spins such as of the hydrogen nuclei (protons), but electron spins may also be concerned. The magnetization is locally influenced by application of the position-dependent field patterns. Subsequently, the transmission coils apply the RF excitation pulse to the examination space in which the part to be imaged of the patient to be examined is situated. The RF excitation pulse excites the spins in the region of interest, i.e. the net magnetization then performs a precessional motion about the direction of the main field. During this operation those spins are excited which have a

Larmor frequency within the frequency band of the RF excitation pulse in the main field. However, it is also very well possible to excite the spins in a part of the body which part is much larger than a thin slice; for example, the spins can be excited in a three-dimensional part which extends substantially in three directions in the body. After the RF excitation, the spins slowly return to their initial state and the macroscopic magnetization returns to its (thermal) state of equilibrium. The relaxing spins then emit magnetic resonance signals.

In contradistinction to a conventional MR imaging system as described in principle above the MR imaging system according to the present invention contains N subsystems that can induce purposely and substantially position-dependent field patterns. The expression "field pattern" is meant to be in more general terms for what is conventionally mentioned "gradient" or "main field" which are normally linear and homogeneous. The field patterns used in this invention are substantially non-linear. A further important feature of the method is that the number N of field patterns is always larger than 3. In addition, at least $N - 1$ field patterns are independently controllable in their field strength, i.e. the strength of the created pattern is controlled by the current applied to the particular subsystem, which is called here "switchable".

In the sequel, these field patterns are called $G_0(x, y, z)$, $G_1(x, y, z)$, $G_2(x, y, z)$, ..., $G_{N-1}(x, y, z)$, or for simplicity G_0 , G_1 , G_2 , ..., G_{N-1} . All of them are switchable, except the main field pattern G_0 which is comparable with the main field B_0 in a conventional MR system. A conventional MR system may be regarded as one where $G_1(x, y, z) = G_x(x, y, z) = x$, ..., $G_3(x, y, z) = G_z(x, y, z) = z$ and there is no other purposely position-dependent field.

The acquisition of data on such a system is performed by using any known MR method as described above in connection with Fig. 1, whereas G_1 , G_2 , G_3 , G_4 , ... are switched as in "normal" MR acquisition systems for G_x , G_y and G_z . As a main difference, this is an experiment of higher dimensionality, e.g. using four encoding dimensions to acquire information from a three-dimensional human body. In order to compensate for this gross increase in scanning time as more data must be sampled, a further important characteristic of the present method is that the acquired data is grossly undersampled in analogy to the well-known SENSE technique (see e.g. K. Pruessmann et. al. in Proc. ISMRM, 1998, abstracts pp. 579, 799, 803 and 2087).

The reconstruction is formed by following elements:

1. The knowledge of the mapping of co-ordinates (x, y, z) in real space to G -space. For better understanding of this notion suppose that each of the subsystems is driven by a unit current (e.g. 1A), and, if applicable the steady-state subsystem G_0 is driven by its standard

current. Then every point in real space will experience a given field component caused by the system G_0 , some other field component caused by the system G_1 , etc. Thus any specific point (x, y, z) will be mapped to a point $(g_0, g_1, g_2, \dots, g_{N-1})$ in G-space, as is depicted in Fig. 4. The mapping is, in principle, known from the system design.

- 5 2. The acquired raw MR-data can be seen as an N-dimensional set of data in the $(k_0, k_1, k_2, \dots, k_{N-1})$ -space in analogy to (k_x, k_y, k_z) . That data can be transformed by Fourier transformation to G-space (cf. "image space").
3. Some pairs of (x, y, z) locations will map to identical $(g_0, g_1, g_2, \dots, g_{N-1})$ – co-ordinates due to folding. These ambiguities can be resolved by knowledge of the coil-sensitivity
- 10 profiles which technique is known from SENSE, or by continuity constraints or by known sparsity of the object, e.g. when vessels are imaged.

For better understanding of the present method consider now the simplified case of an MR imaging system designed to image an object in only one dimension. The imaging system is depicted in Fig. 2 wherein G_0 is a circular coil system and G_1 is a straight

15 lead that is close to the one-dimensional object 31, i.e. (part of) the patient. It is further assumed that a strong constant field is present, aligned with the main direction of the object 31. In Fig. 3 the field strength B of both field patterns G_0 and G_1 are depicted with respect to the x-axis. Given these field patterns, one can draw the locus 32 of the one-dimensional

object in the two-dimensional G-space as shown in Fig. 4.

20 In principle on this system a normal 2-dimensional MR experiment can be applied, whereas the current in G_0 will be driven as a readout field pattern and the current in G_1 as a phase-encoding field pattern. After Fourier transformation a 2-dimensional image will be obtained, of which only a small part would be nonzero, i.e. the locus of the object 31. However, such a simple approach would have the significant drawback of a gross increase in

25 scanning time. In above example 256^2 measurements points are needed to resolve approximately 256 points of the patient. In order to overcome this disadvantage, a gross subsampling of G-space can be applied. The result can nevertheless be reconstructed, as large areas of G-space are factually empty. In Fig. 5 the folding of the locus 32a, 32b, ..., 32f of object 31 in G-space due to undersampling is shown. Large parts of the object 31 can be

30 uniquely extracted from G-space, but on some points there may be an overlap. This can be intrinsic as shown at circle 33 or caused by undersampling as shown at full bullet 34. The intrinsic ambiguity may be caused by system design (e.g. due to current lead constraints, two points of the object have exactly the same magnetic field under all circumstances etc.). However, it is more likely that the ambiguity is caused by undersampling. Both ambiguities

can be resolved in several manners. The first one is to apply the knowledge on coil sensitivity patterns, if the object has been acquired using an array of coils – like in the SENSE method mentioned above. A second solutions is the use of continuity constraints e.g. by assuming that is unlikely that an object will show a distinct local detail at exactly a particular cross-over position. Especially if such a system is used for angiographic purposes, the knowledge can be used that large parts of the interesting object will contain only very little signal at all.

This more theoretical approach can be understood better by way of the following model as depicted in Fig. 6. If a more or less linear field pattern system in direction “feet-head” (z-direction) would be used like e.g. the open magnet system as shown and described in Fig. 4 of WO-A-00/33100, the field pattern system must store a huge amount of energy which only can be arranged by very expensive electric amplifiers, which imply very strong field variations at about 1 meter off the centre of the MR system. Therefore, nervous stimulation will occur with the patient and the operator. It should be clear that such large fields with high energy storage will make the practical use of linear field patterns in z-direction almost impossible. An alternative to a linear field pattern in z-direction can be obtained by a system of parallel conductor systems, e.g. the four systems A, B, C and D, each of which has a design similar as the main magnet field of the system as shown in Fig. 2 of WO-A-00/33100, whereas the “switched” magnetic fields are substantially shorter in z-direction. The four conductor systems A, B, C and D are identical, but provided equidistantly at different positions along the z-axis. Each of the conductor systems A, B, C and D can be controlled separately. The field pattern of each of the conductor systems is shown in Fig. 6, whereas B_{gs} is the extra field “switched” by the conductor system at a unit of current. Since the field pattern of the conductor systems is a Gaussian function and thus not linear in z-direction, it is definitely not a “gradient” as known from the usual MR systems. However, the conductor systems can be used similar as “gradients” in the classical manner since they have a pattern which varies continuously in z-direction and can be switched on and off. It is now possible to perform two different MR sequences in z-direction, whereas in x- and y-direction normal gradients are used. The first sequence the combination $G_1 = (A + B - C - D)$ is applied and the second sequence the combination $G_2 = (-A + B + C - D)$ is applied. For each of the sequence the data received by the receiver antennae will be reconstructed in a normal manner, e.g. according to a 3-dimensional Fast Fourier Transformation (FFT). For each of the (x, y) coordinate of the patient a graph in $G_1 - G_2$ space according to Fig. 7 will be obtained which is commensurate to a straight line parallel to the z-axis. Concerning the axis G_1 and G_2 one should realise that it represents the magnetic field of the combination of coils

or conductor systems A, B, C and D excited by a unit of electric current. So, the first MR sequence is measuring the equidistant points along this axis (for all x and y coordinates of that point along the z-axis). The curve in Fig. 7 is the locus of all combinations which are possible within the patient's body. For instance, the point at the far left of the patient (circle 5 35 in Fig. 6) which is almost only excited by conductor system A, experiences a negative magnetic field for G_2 and a positive magnetic field for G_1 . The results of the mentioned measuring sequences represent in fact a projection of the patient curve on the axis. Thus, the measurement of point 36 ("X") at the G_1 axis is a sum of images within the patient at two different positions 37 ("full bullets"), as can be seen in Fig. 8. The two points can be derived 10 from the measurement points 36 by knowledge of the sensitivity of the RF coils in analogy to the SENSE method. Since the number of measured points on the curve is essentially identical to the number of unknown variables, the calculation should be performed with all other measured variables. In the example showed in Fig. 7 the number of measurement points 37 ("full bullets") is seven and also the number of unknown variables 36 ("X") is seven – see 15 Fig. 9.

With the system described above one can design an MR system with imperfect coils having highly non-linear field patterns – comparable with "gradients" in classical terms – in order to obtain a relatively inexpensive system of large field-of-view. Important prerequisites for such a system are that the position-dependent field patterns and the coil 20 sensitivity patterns, i.e. the proper features of the RF coil system, should be known.

CLAIMS:

1. A magnetic resonance imaging method for forming an image of an object, wherein
 - a stationary magnetic field (G_0) and temporary magnetic fields having a position dependent field pattern (G_1, G_2, G_3, \dots) are applied,
 - 5 - magnetic resonance signals are acquired by at least one receiver antenna,
 - spins are excited in a part of the object,
 - MR signals are acquired during application of the position-dependent field patterns (G_1, G_2, \dots)
 - a magnetic resonance image is derived from the sampled magnetic resonance
 - 10 signals, whereas
 - the position dependent field patterns (G_1, G_2, \dots) are substantially non-linear,
 - the number N of total field patterns is larger than 3, and at least $N - 1$ field patterns are independently controllable in field strength.
- 15 2. A method as claimed in Claim 1, wherein the magnetic resonance signals are acquired in a sub-sampling fashion and the magnetic resonance image is derived from the sub-sampled magnetic resonance signals.
- 20 3. A method as claimed in Claim 2, wherein the magnetic resonance signals are sub-sampled by means of an array of receiving antennae and the magnetic resonance image is derived from the sub-sampled magnetic resonance signals on the basis of the spatial sensitivity profiles of the array of receiving antennae.
- 25 4. A method as claimed in Claim 2, characterized in that fold-over artefacts are distinguished by continuity constraints of the object to be imaged.
5. A method as claimed in Claim 2, characterized in that fold-over artefacts are distinguished and discarded by knowledge of the sparsity of the object to be imaged.

6. A magnetic resonance imaging apparatus for obtaining an MR image from a plurality of signals comprising:

- means (10, 12) for applying a stationary magnetic field and temporary, substantially non-linear magnetic fields having a position dependent field pattern,
- 5 - at least one receiving antenna (13, 15) for acquiring magnetic resonance signals, during application of position-dependent field patterns (G_1, G_2, \dots),
- means (13) for excitation of spins in a part of the object,
- means (25) for deriving a magnetic resonance image from the sampled magnetic resonance signals,

10 wherein the magnetic field means are arranged to obtain substantially non-linear magnetic fields, whereas the number N of total field patterns is larger than 3, and at least $N - 1$ field patterns are independently controllable in field strength.

7. An apparatus as claimed in Claim 6, wherein means are provided for acquiring
15 the magnetic resonance signals in a sub-sampling fashion and means for deriving the magnetic resonance image from the sub-sampled magnetic resonance signals.

8. An apparatus as claimed in Claim 7, wherein an array of receiver antennae and means for determining the sensitivity profiles of the receiver antennae are provided.

20

9. A computer program product stored on a computer usable medium for forming an image by means of the magnetic resonance method, comprising a computer readable program means for causing the computer to control the execution of:

- applying a stationary magnetic field and temporary magnetic fields having a
25 position dependent field pattern, whereas the magnetic fields are substantially non-linear and the number N of total field patterns is larger than 3,
- acquiring magnetic resonance signals by at least one receiver antenna,
- exciting spins in a part of the object,
- acquiring MR signals during application of position-dependent field patterns
30 (G_1, G_2, \dots),
- deriving a magnetic resonance image is from the sampled magnetic resonance signals,

controlling at least $N - 1$ field patterns independently in their field strength.

10. A computer program product as claimed in Claim 9, additionally acquiring the magnetic resonance signals in a sub-sampling fashion and deriving the magnetic resonance image from the sub-sampled magnetic resonance signals.

1/5





FIG. 1

2/5



$\odot G_0$

FIG.2




FIG.3




FIG. 4




FIG. 5

4/5




FIG. 6




FIG. 7

5/5




FIG. 8




FIG. 9

INTERNATIONAL SEARCH REPORT

national Application No

PCT/IB 03/06306

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 G01R33/565 G01R33/561

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 G01R

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, BIOSIS, EMBASE, INSPEC, COMPENDEX, MEDLINE, WPI Data, PAJ

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	LAI C-M: "RECONSTRUCTING NMR IMAGES FROM PROJECTIONS UNDER INHOMOGENEOUS MAGNETIC FIELD AND NON-LINEAR FIELD GRADIENTS" PHYSICS IN MEDICINE AND BIOLOGY, TAYLOR AND FRANCIS LTD. LONDON, GB, vol. 28, no. 8, August 1983 (1983-08), pages 925-938, XP001026614 ISSN: 0031-9155 the whole document	1,6,9,10
A	US 4 651 098 A (ABE ZENWEMON ET AL) 17 March 1987 (1987-03-17) column 2, line 17 - line 52 column 5, line 48 - column 6, line 23 column 12, line 16 - line 34 ----- -/--	1-10



Further documents are listed in the continuation of box C.



Patent family members are listed in annex.

* Special categories of cited documents:

A document defining the general state of the art which is not considered to be of particular relevance

E earlier document but published on or after the international filing date

L document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

O document referring to an oral disclosure, use, exhibition or other means

P document published prior to the international filing date but later than the priority date claimed

T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

G document member of the same patent family

Date of the actual completion of the international search

26 April 2004

Date of mailing of the international search report

17/06/2004

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+31-70) 340-3016

Authorized officer

Skalla, J

INTERNATIONAL SEARCH REPORT

International Application No.
PCT/IB 03/06306

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT		
Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	<p>PRUESSMANN K P ET AL: "SENSE: SENSITIVITY ENCODING FOR FAST MRI" MAGNETIC RESONANCE IN MEDICINE, ACADEMIC PRESS, DULUTH, MN, US, vol. 42, no. 5, November 1999 (1999-11), pages 952-962, XP000866655 ISSN: 0740-3194 the whole document</p>	1-10
A	<p>US 4 672 320 A (KOHNO HIDEKI ET AL) 9 June 1987 (1987-06-09) column 3, line 38 - line 56 column 4, line 4 - line 21 column 12, line 28 - line 52</p>	1-10
A	<p>US 5 886 524 A (KRIEG ROBERT) 23 March 1999 (1999-03-23) column 1, line 45 - column 2, line 38 column 6, line 17 - line 58</p>	1-10

INTERNATIONAL SEARCH REPORT

information on patent family members

national Application No

PCT/IB 03/06306

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 4651098	A	17-03-1987	JP 1617119 C	12-09-1991
			JP 2063009 B	27-12-1990
			JP 60080747 A	08-05-1985
			GB 2149921 A , B	19-06-1985
US 4672320	A	09-06-1987	JP 1756316 C	23-04-1993
			JP 4048451 B	06-08-1992
			JP 59190643 A	29-10-1984
			DE 3484024 D1	07-03-1991
			EP 0122593 A2	24-10-1984
US 5886524	A	23-03-1999	DE 19540837 A1	07-05-1997
			JP 9122102 A	13-05-1997

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☒ FADED TEXT OR DRAWING
- ☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☒ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☒ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.